


129


Verteilerleiste 3fach  
3-connection block  
Collettore di distribuzione



| ITV   | G    | H  | B  | L   | L1   | L2 | A1 | Ød  |
|-------|------|----|----|-----|------|----|----|-----|
| 12900 | M5   | 15 | 15 | 40  | 10   | 10 | 32 | 3,4 |
| 12901 | G1/8 | 20 | 20 | 56  | 13,5 | 17 | 46 | 4,4 |
| 12902 | G1/4 | 30 | 30 | 89  | 20   | 29 | 74 | 6,4 |
| 12903 | G3/8 | 40 | 30 | 85  | 20   | 26 | 72 | 6,4 |
| 12904 | G1/2 | 40 | 30 | 105 | 25   | 32 | 90 | 6,4 |

131

Durchgangsleiste  
Through-going block  
Collettore passante



| ITV   | G    | G1   | B  | H  | L1  | L2 | L3 | L   | N |
|-------|------|------|----|----|-----|----|----|-----|---|
| 60411 | G1/4 | G1/8 | 20 | 30 | 4,5 | 18 | 18 | 54  | 2 |
| 60412 | G1/4 | G1/8 | 20 | 30 | 4,5 | 18 | 18 | 72  | 3 |
| 60413 | G1/4 | G1/8 | 20 | 30 | 4,5 | 18 | 18 | 90  | 4 |
| 60414 | G1/4 | G1/8 | 20 | 30 | 4,5 | 18 | 18 | 108 | 5 |
| 60415 | G3/8 | G1/4 | 25 | 40 | 8,5 | 24 | 22 | 68  | 2 |
| 60416 | G3/8 | G1/4 | 25 | 40 | 8,5 | 24 | 22 | 92  | 3 |
| 60417 | G3/8 | G1/4 | 25 | 40 | 8,5 | 24 | 22 | 116 | 4 |
| 60418 | G3/8 | G1/4 | 25 | 40 | 8,5 | 24 | 22 | 140 | 5 |